



**Faculty of Electrical Engineering**

**VOLTAGE INSTABILITY ANALYSIS OF ELECTRIC POWER  
SYSTEMS USING ARTIFICIAL NEURAL NETWORK BASED  
APPROACH**

**Ahmad Fateh bin Mohamad Nor**

**Doctor of Philosophy**

**2017**

**VOLTAGE INSTABILITY ANALYSIS OF ELECTRIC POWER SYSTEMS USING  
ARTIFICIAL NEURAL NETWORK BASED APPROACH**

**AHMAD FATEH BIN MOHAMAD NOR**

**A thesis submitted  
in fulfillment of the requirements for the degree of Doctor of Philosophy**

**Faculty of Electrical Engineering**

**UNIVERSITI TEKNIKAL MALAYSIA MELAKA**

**2017**

## DECLARATION

I declare that this thesis entitled “Voltage Instability Analysis of Electric Power Systems Using Artificial Neural Network Based Approach” is the result of my own research except as cited in the references. The thesis has not been accepted for any degree and is not concurrently submitted in candidature of any other degree.

Signature : .....

Name : Ahmad Fateh bin Mohamad Nor

Date : .....

## APPROVAL

I hereby declare that I have read this thesis and in my opinion this thesis is sufficient in terms of scope and quality for the award of Doctor of Philosophy.

Signature : .....

Supervisor Name : Professor Dr. Marizan bin Sulaiman

Date : .....

## **DEDICATION**

To my beloved mother, father, brother and sisters.

## ABSTRACT

Voltage instability analysis in electric power system is one of the most important factors in order to maintain the equilibrium of the electric power system. A power system is said to be experiencing voltage instability whenever the system is not able to maintain the voltage at all buses in the system remain the same after the system is being subjected to a disturbance. Voltage instability can lead to total system blackout. Therefore, it is important to implement voltage instability analysis in order to make sure that the voltage level at all buses is at stable state. Even though the research regarding voltage instability analysis has been carried out for decades, there is still room for improvement especially in terms of accuracy and time execution. The research work presented in this thesis is about the analysis of voltage instability of electric power system by using reactive power-voltage (QV) and real power-voltage (PV) curves. PV and QV curves are very important for calculating voltage instability indices. These voltage instability indices are voltage stability margin (VSM) and load power margin (LPM). VSM can be divided into two indices which are VSM for real and reactive power of load, VSM (P) and VSM (Q). Similarly, there are two categories of LPM which are LPM of real power and reactive power of load, LPM (P) and LPM (Q). Besides that, modal analysis technique is used in this research for determining the weakest load buses in the electrical power system. This research will explore the implementation of real power (P) modal analysis technique in addition to the reactive power (Q) modal analysis technique. It was found that reactive power (Q) of load gives more effects towards the stability of the system voltages than real power (P) of load. Subsequently, Artificial Neural Network (ANN) and Adaptive Neuro-Fuzzy Inference System (ANFIS) are used for providing the target values of VSM (P), VSM (Q), LPM (P) and LPM (Q). The accuracy and computing time of both ANN and ANFIS are being recorded and compared. The research showed that the accuracy and computing time of ANFIS are better than ANN's. Finally, Probabilistic Neural Network is applied for classifying the voltage instability indices. IEEE 14, 30 and 39-Bus Test Power System were selected as the reference power systems in this research. The load flow analyses were simulated by using Power World Simulator software version 16. Both Q and P modal analysis were done by using MATLAB application software.

## ABSTRAK

*Analisa ketidakstabilan voltan dalam sistem kuasa elektrik adalah salah satu faktor yang paling penting untuk mengekalkan keseimbangan dalam sistem kuasa elektrik. Sesebuah sistem kuasa dikatakan mengalami ketidakstabilan voltan apabila sistem tersebut tidak mampu untuk memastikan nilai voltan pada semua bus dalam sistem tidak berubah selepas sistem tersebut mengalami gangguan. Ketidakstabilan voltan boleh menyebabkan terputusnya bekalan elektrik secara besar-besaran. Oleh itu, keperluan untuk menganalisis ketidakstabilan voltan adalah sangat penting bagi memastikan tahap voltan di semua bus berada pada keadaan stabil. Walaupun penyelidikan mengenai analisa ketidakstabilan voltan telah dijalankan sejak beberapa dekad yang lalu, masih terdapat ruang untuk penambahbaikan terutama dari segi ketepatan dan masa pelaksanaan. Kerja-kerja penyelidikan yang dibentangkan di dalam tesis ini adalah mengenai analisa ketidakstabilan voltan sistem kuasa elektrik dengan menggunakan lengkungan kuasa aktif-voltan (PV) dan kuasa reaktif-voltan (QV). Lengkungan PV dan QV adalah sangat penting untuk mengira indeks ketidakstabilan voltan. Indeks-indeks ketidakstabilan voltan tersebut adalah margin kestabilan voltan (VSM) dan margin kuasa beban (LPM). VSM ini boleh dibahagikan kepada dua indeks iaitu VSM untuk kuasa sebenar, VSM (P) dan VSM untuk kuasa reaktif, VSM (Q). Begitu juga untuk LPM di mana terdapat dua kategori LPM iaitu LPM untuk kuasa sebenar, LPM (P) dan LPM untuk kuasa reaktif, LPM (Q). Selain itu, teknik analisis modal digunakan dalam kajian ini untuk menentukan bus beban yang paling lemah di dalam sistem kuasa elektrik. Kajian ini akan meneroka pelaksanaan teknik analisis modal kuasa sebenar (P) sebagai tambahan kepada teknik analisis modal kuasa reaktif (Q). Adalah didapati daripada kajian ini bahawa beban kuasa reaktif (Q) memberi lebih kesan ke arah kestabilan voltan di dalam system dibandingkan dengan beban kuasa sebenar (P). Berikutnya, Artificial Neural Network (ANN) dan Inference Adaptive Neuro-Fuzzy System (ANFIS) digunakan untuk meramalkan nilai sasaran VSM (P), VSM (Q), LPM (P) dan LPM (Q). Ketepatan dan masa pelaksanaan oleh ANN dan ANFIS direkodkan dan dianalisa. Kajian menunjukkan bahawa ketepatan dan masa pengiraan ANFIS adalah lebih baik daripada ANN. Akhir sekali, Probabilistic Neural Network (PNN) digunakan untuk mengklasifikasikan indeks ketidakstabilan voltan. IEEE 14, 30 dan 39 sistem kuasa telah dipilih sebagai sistem kuasa rujukan dalam kajian ini. Analisis aliran beban telah disimulasikan dengan menggunakan perisian Power World Simulator versi 16. Kedua-dua Q dan analisis modal P telah dilakukan dengan menggunakan perisian aplikasi MATLAB.*

## ACKNOWLEDGEMENTS

Alhamdulillah, all the praises and thanks be to Allah for all of His infinite blessings.

First and foremost, I would like to express my sincere acknowledgement to my supervisor, Prof. Dr. Marizan bin Sulaiman for his excellent supervision and never-ending support. His guidance and advices are very helpful and useful in completing this research. I could not have imagined having a better supervisor for my study. Furthermore, special thanks are in order to my co-supervisor, Dr. Aida Fazliana binti Abdul Kadir for her kind guidance and great cooperation.

I would also like to express my gratitude to the Universiti Teknikal Malaysia Melaka (UTeM) especially to the Faculty of Electrical Engineering and to the Centre of Graduate Studies for giving me the opportunity to pursue the degree of Doctor of Philosophy (PhD.) in this beautiful university. Nevertheless, all of the UTeM staffs also deserve my appreciation, as they work hard to help the students to reach their goals.

Besides that, I would like to thank the Ministry of Higher Education Malaysia for providing the financial support under the MyBrain15 program. Sincere thanks to all of my friends especially my lab mates in the Energy and Power System (EPS) Research Laboratory, Center of Excellent for Robotics and Industrial Automation (CeRIA) for all the help, friendships and sweet memories.

Last but most importantly, my deepest gratitude goes to the closest people to my heart, my beloved parents, Associate Prof. Dr. Mohamad Nor bin Mohamad Than and Mrs. Norlida binti Shaharuddin, my brother Ahmad Fadhli, my sister in law Dr. Akmal Hanisah, my sister Nabila, my niece Faiha Adreena and all of my family members for their endless love, prayers, supports, motivation, patience, care and encouragement. Thank you very much once again to every single person who directly or indirectly contributed to this research.



## TABLE OF CONTENTS

<b>DECLARATION</b>	<b>i</b>
<b>APPROVAL</b>	<b>ii</b>
<b>DEDICATION</b>	<b>iii</b>
<b>ABSTRACT</b>	<b>i</b>
<b>ABSTRAK</b>	<b>ii</b>
<b>ACKNOWLEDGEMENTS</b>	<b>iii</b>
<b>TABLE OF CONTENTS</b>	<b>iv</b>
<b>LIST OF TABLES</b>	<b>viii</b>
<b>LIST OF FIGURES</b>	<b>xiii</b>
<b>LIST OF APPENDICES</b>	<b>xix</b>
<b>LIST OF ABBREVIATIONS/SYMBOLS</b>	<b>xx</b>
<b>LIST OF PUBLICATIONS</b>	<b>xxii</b>
<b>CHAPTER</b>	
<b>1. INTRODUCTION</b>	<b>24</b>
1.0 Introduction	24
1.1 Background	24
1.2 Motivation of Research	26
1.3 Problem Statement	26
1.4 Objectives of Research	28
1.5 Scopes of Research	29
1.6 Contributions of Research	29
1.7 Organization of Thesis	30
<b>2. LITERATURE REVIEW</b>	<b>31</b>
2.0 Introduction	31
2.1 Power System Stability	31
2.2 Voltage Instability	33
2.3 Voltage Instability Analysis Methods	35
2.3.1 PV and QV Curves	36
2.3.2 Modal Analysis	37
2.4 Artificial Neural Network in Voltage Instability Analysis	38
2.5 Adaptive Network Fuzzy Inference System in Voltage Instability Analysis	40
2.6 Probabilistic Neural Network in Voltage Instability Analysis	41
2.7 Critical Review of the Literature	41

2.8	Summary	49
<b>3.</b>	<b>RESEARCH METHODOLOGY</b>	<b>51</b>
3.0	Introduction	51
3.1	IEEE Test Power System	51
3.1.1	IEEE 14-Bus Test Power System	52
3.1.2	IEEE 30-Bus Test Power System	52
3.1.3	IEEE 39-Bus Test Power System	53
3.2	Voltage Instability Analysis Research Methodology	54
3.3	PV and QV Curves Technique	57
3.3.1	Voltage Stability Margin	57
3.3.2	Load Power Margin (LPM)	59
3.4	Modal Analysis Technique	61
3.4.1	Q Modal Analysis Technique	62
3.4.1.1	Reduced Jacobian Matrix (Jr)	62
3.4.1.2	Determination of the Most Critical Mode	63
3.4.1.3	Bus Participation Factor	63
3.4.2	P Modal Analysis Technique	64
3.4.2.1	Reduced Jacobian Matrix	64
3.5	Application of Artificial Neural Network	65
3.5.1	Fundamental Theory of ANN	65
3.5.2	Multilayer Perceptron with Backpropagation ANN Networks	67
3.5.3	Executing MLBP-ANN in MATLAB	69
3.6	Adaptive Neuro-Fuzzy Inference System	71
3.6.1	ANFIS Structure	71
3.6.2	ANFIS Learning Algorithm	74
3.6.3	Application of ANFIS in MATLAB	75
3.7	Generation of Training Data	77
3.8	Performance Measurement	78
3.8.1	Mean Squared Error (MSE)	78
3.8.2	Regression Analysis	78
3.9	Probabilistic Neural Network (PNN)	79
3.9.1	Probabilistic neural network (PNN) Architecture	79
3.9.2	Application of PNN in MATLAB	80
3.10	Summary	83
<b>4.</b>	<b>RESULTS AND DISCUSSION: VOLTAGE INSTABILITY ANALYSIS</b>	<b>84</b>
4.0	Introduction	84
4.1	Calculation of VSM and LPM Values	84
4.1.1	IEEE 14-Bus Test Power System	85
4.1.1.1	VSM (P)	85
4.1.1.2	VSM (Q)	86
4.1.1.3	LPM (P)	87
4.1.1.4	LPM (Q)	88

4.1.2	IEEE 30-Bus Test Power System	89
4.1.2.1	VSM (P)	89
4.1.2.2	VSM (Q)	90
4.1.2.3	LPM (P)	91
4.1.2.4	LPM (Q)	93
4.1.3	IEEE 39-Bus Test Power System	94
4.1.3.1	VSM (P)	94
4.1.3.2	VSM (Q)	95
4.1.3.3	LPM (P)	97
4.1.3.4	LPM (Q)	98
4.2	Results of Q and P Modal Analysis Technique	99
4.2.1	IEEE 14-Bus Test Power System	100
4.2.1.1	Q Modal Analysis Technique	100
4.2.1.2	P Modal Analysis Technique	101
4.2.2	IEEE 30-Bus Test Power System	102
4.2.2.1	Q Modal Analysis Technique	102
4.2.2.2	P Modal Analysis Technique	104
4.2.3	IEEE 39-Bus Test Power System	105
4.2.3.1	Q Modal Analysis Technique	105
4.2.3.2	P Modal Analysis Technique	107
4.3	Determination of The Weakest Load Buses Based on VSM/LPM Values and QV/P modal analysis Technique	108
4.3.1	IEEE 14-Bus Test Power System Weak Buses Determination	109
4.3.2	IEEE 30-Bus Test Power System Weak Buses Determination	110
4.3.3	IEEE 39-Bus Test Power System Weak Buses Determination	111
4.4	Summary	113
<b>5.</b>	<b>PREDICTION AND CLASSIFICATION OF VOLTAGE INSTABILITY INDICES</b>	<b>114</b>
5.1	Introduction	114
5.2	Prediction of VSM and LPM Values by MLPBP-ANN and ANFIS	114
5.2.1	IEEE 14-Bus Test Power System	114
5.2.1.1	VSM (P) Prediction Values	115
5.2.1.2	VSM (Q) Prediction Values	116
5.2.1.3	LPM (P) Prediction Values	118
5.2.1.4	LPM (Q) Prediction Values	119
5.2.1.5	Mean Squared Error (MSE)	120
5.2.1.6	Regression	126
5.2.1.7	Computing Time	134
5.2.2	IEEE 30-Bus Test Power System Prediction Results	140
5.2.2.1	VSM (P) Prediction Values	140
5.2.2.2	VSM (Q) Prediction Values	141
5.2.2.3	LPM (P) Prediction Values	143
5.2.2.4	LPM (Q) Prediction Values	144

5.2.2.5	Mean Squared Error (MSE)	145
5.2.2.6	Regression	150
5.2.2.7	Computing Time	159
5.2.3	IEEE 39-Bus Test Power System	164
5.2.3.1	VSM (P) Prediction Values	165
5.2.3.2	VSM (Q) Prediction Values	166
5.2.3.3	LPM (P) Prediction Values	168
5.2.3.4	LPM (Q) Prediction Values	169
5.2.3.5	Mean Squared Error (MSE)	170
5.2.3.6	Regression	176
5.2.3.7	Computing Time	184
5.3	Classifications of VSM and LPM Values by PNN	190
5.3.1	IEEE 14-Bus Test Power System	190
5.3.1.1	VSM (P)	190
5.3.1.2	VSM (Q)	193
5.3.1.3	LPM (P)	195
5.3.1.4	LPM (Q)	198
5.3.2	IEEE 30-Bus Test Power System	200
5.3.2.1	VSM (P)	200
5.3.2.2	VSM (Q)	203
5.3.2.3	LPM (P)	205
5.3.2.4	LPM (Q)	208
5.3.3	IEEE 39-Bus Test Power System	210
5.3.3.1	VSM (P)	210
5.3.3.2	VSM (Q)	213
5.3.3.3	LPM (P)	216
5.3.3.4	LPM (Q)	219
5.4	Summary	221
<b>6.</b>	<b>CONCLUSION AND RECOMMENDATIONS FOR FUTURE WORKS</b>	<b>222</b>
6.1	Introduction	222
6.2	Conclusion of Research	222
6.3	Achievement of Research Objectives	223
6.4	Significance of Research Findings	224
6.5	Suggestions for Future Research	225
	<b>REFERENCES</b>	<b>226</b>
	<b>APPENDICES</b>	<b>245</b>

## LIST OF TABLES

TABLE	TITLE	PAGE
2.1:	Critical Review of The Relevant Literatures	42
3.1:	List of Inputs for MLBP-ANN	67
4.1:	VSM (P) Calculation Values for IEEE 14-Bus Test Power System	85
4.2:	VSM (Q) Calculation Values for IEEE 14-Bus Test Power System	86
4.3:	LPM (P) Calculation Values for IEEE 14-Bus Test Power System	87
4.4:	LPM (Q) Calculation Values for IEEE 14-Bus Test Power System	88
4.5:	VSM (P) Calculation Values for IEEE 30-Bus Test Power System	89
4.6:	VSM (Q) Calculation Values for IEEE 30-Bus Test Power System	91
4.7:	LPM (P) Calculation Values for IEEE 30-Bus Test Power System	92
4.8:	LPM (Q) Calculation Values for IEEE 30-Bus Test Power System	93
4.9:	VSM (P) Calculation Values for IEEE 39-Bus Test Power System	94
4.10:	VSM (Q) Calculation Values for IEEE 39-Bus Test Power System	95
4.11:	LPM (P) Calculation Values for IEEE 39-Bus Test Power System	97
4.12:	LPM (Q) Calculation Values for IEEE 39-Bus Test Power System	98
4.13:	Participation Factor from Q Modal Analysis	100
4.14:	Participation Factor from P Modal Analysis	101
4.15:	Participation Factor from Q Modal Analysis	102
4.16:	Participation Factor from P Modal Analysis	104
4.17:	Participation Factor from Q Modal Analysis	105

4.18:	Participation Factor from P Modal Analysis	107
4.19:	Summary of Weakest Bus for IEEE 14-Bus Test Power System	109
4.20:	Summary of Weakest Bus for IEEE 30-Bus Test Power System	110
4.21:	Summary of Weakest Bus for IEEE 39-Bus Test Power System	112
5.1:	VSM (P) Prediction Values by MLPBP-ANN and ANFIS	115
5.2:	VSM (Q) Prediction Values by MLPBP-ANN and ANFIS	116
5.3:	LPM (P) Prediction Values by MLPBP-ANN and ANFIS	118
5.4:	LPM (Q) Prediction Values by MLPBP-ANN and ANFIS	119
5.5:	The MSE Values for both MLBP-ANN and ANFIS in Predicting VSM (P) Values of Weak Buses In the IEEE 14-Bus Test Power System	121
5.6:	The MSE Values for MLBP-ANN and ANFIS in Predicting VSM (Q) Values of Weak Buses In the IEEE 14-Bus Test Power System	122
5.7:	The MSE Values for both MLBP-ANN and ANFIS in Predicting LPM (P) Values of Weak Buses In the IEEE 14-Bus Test Power System	123
5.8:	The MSE Values for both MLBP-ANN and ANFIS in Predicting LPM (Q) Values of Weak Buses In the IEEE 14-Bus Test Power System	125
5.9:	VSM (P) Predictions Time by MLBP-ANN and ANFIS for IEEE 14-Bus Test Power System	134
5.10:	VSM (Q) Predictions Time by MLBP-ANN and ANFIS for IEEE 14-Bus Test Power System	136
5.11:	LPM (P) Predictions Time by MLBP-ANN and ANFIS for IEEE 14-Bus Test Power System	137
5.12:	LPM (Q) Predictions Time by MLBP-ANN and ANFIS for IEEE 14-Bus Test Power System	139
5.13:	VSM (P) Prediction Values by MLPBP-ANN and ANFIS	140
5.14:	VSM (Q) Prediction Values by MLPBP-ANN and ANFIS	141
5.15:	LPM (P) Prediction Values by MLPBP-ANN and ANFIS	143
5.16:	LPM (Q) Prediction Values by MLPBP-ANN and ANFIS	144

5.17:	The MSE Values for both MLBP-ANN and ANFIS in Predicting VSM (P) Values of Weak Buses In the IEEE 30-Bus Test Power System	146
5.18:	The MSE Values for both MLBP-ANN and ANFIS in Predicting VSM (Q) Values of Weak Buses In the IEEE 30-Bus Test Power System	147
5.19:	The MSE Values for both MLBP-ANN and ANFIS in Predicting LPM (P) Values of Weak Buses In the IEEE 30-Bus Test Power System	148
5.20:	The MSE Values for both MLBP-ANN and ANFIS in Predicting LPM (Q) Values of Weak Buses In the IEEE 14-Bus Test Power System	149
5.21:	VSM (P) Computing Time by MLBP-ANN and ANFIS for IEEE 30-Bus Test Power System	159
5.22:	VSM (Q) Computing Time by MLBP-ANN and ANFIS for IEEE 30-Bus Test Power System	161
5.23:	LPM (P) Computing Time by MLBP-ANN and ANFIS for IEEE 30-Bus Test Power System	162
5.24:	LPM (Q) Computing Time by MLBP-ANN and ANFIS for IEEE 30-Bus Test Power System	163
5.25:	VSM (P) Prediction Values by MLPBP-ANN and ANFIS for IEEE 39-Bus Test Power System	165
5.26:	VSM (Q) Prediction Values by MLPBP-ANN and ANFIS for IEEE 39-Bus Test Power System	166
5.27:	LPM (P) Prediction Values by MLPBP-ANN and ANFIS for IEEE 39-Bus Test Power System	168
5.28:	LPM (Q) Prediction Values by MLPBP-ANN and ANFIS	169
5.29:	The MSE Values for both MLBP-ANN and ANFIS in Predicting VSM (P) Values of Weak Buses in the IEEE 39-Bus Test Power System	171
5.30:	The MSE Values for both MLBP-ANN and ANFIS in Predicting VSM (Q) Values of Weak Buses in the IEEE 39-Bus Test Power System	172
5.31:	The MSE Values for both MLBP-ANN and ANFIS in Predicting LPM (P) Values of Weak Buses In the IEEE 39-Bus Test Power System	173

5.32:	The MSE Values for both MLBP-ANN and ANFIS in Predicting LPM (Q) Values of Weak Buses In the IEEE 39-Bus Test Power System	175
5.33:	VSM (P) Computing Time by MLBP-ANN and ANFIS for IEEE 39-Bus Test Power System	185
5.34:	VSM (Q) Computing Time by MLBP-ANN and ANFIS for IEEE 30-Bus Test Power System	186
5.35:	LPM (P) Computing Time by MLBP-ANN and ANFIS for IEEE 39-Bus Test Power System	187
5.36:	LPM (Q) Computing Time by MLBP-ANN and ANFIS for IEEE 39-Bus Test Power System	189
5.37:	Results of Bus 14 VSM (P) Training Data Classification by PNN	191
5.38:	Summary of VSM (P) Classifications by PNN for IEEE 14-Bus Power System	192
5.39:	Results of Bus 14 VSM (Q) Training Data Classification by PNN	193
5.40:	Summary of VSM (Q) Classifications by PNN for IEEE 14-Bus Power System	195
5.41:	Results of Bus 14 LPM (P) Training Data Classification by PNN	196
5.42:	Summary of LPM (P) Classifications by PNN for IEEE 14-Bus Power System	197
5.43:	Results of Bus 14 LPM (Q) Training Data Classification by PNN	198
5.44:	Summary of LPM (Q) Classifications by PNN for IEEE 14-Bus Power System	200
5.45:	Results of Bus 30 VSM (P) Training Data Classification by PNN	201
5.46:	Summary of VSM (P) Classifications by PNN for IEEE 30-Bus Power System	202
5.47:	Results of Bus 30 VSM (Q) Training Data Classification by PNN	203
5.48:	Summary of VSM (Q) Classifications by PNN for IEEE 30-Bus Power System	205
5.49:	Results of Bus 30 LPM (P) Training Data Classification by PNN	206
5.50:	Summary of LPM (P) Classifications by PNN for IEEE 30-Bus Power System	207



5.51:	Results of Bus 30 LPM (Q) Training Data Classification by PNN	208
5.52:	Summary of LPM (Q) Classifications by PNN for IEEE 30-Bus Power System	210
5.53:	Results of Bus 12 VSM (P) Training Data Classification by PNN	211
5.54:	Summary of VSM (P) Classifications by PNN for IEEE 39-Bus Power System	213
5.55:	Results of Bus 12 VSM (Q) Training Data Classification by PNN	214
5.56:	Summary of VSM (Q) Classifications by PNN for IEEE 39-Bus Power System	215
5.57:	Results of Bus 12 LPM (P) Training Data Classification by PNN	216
5.58:	Results of LPM (P) Classifications by PNN for IEEE 39-Bus Power System	218
5.59:	Results of Bus 12 LPM (Q) Training Data Classification by PNN	219
5.60:	Results of LPM (Q) Classifications by PNN for IEEE 39-Bus Power System	220

## LIST OF FIGURES

FIGURE	TITLE	PAGE
2.1:	Classification of Power System Stability	32
2.2:	PV and QV Curves	37
2.3:	Basic 3 Layers ANN Configuration	39
2.4:	Configuration of the Multilayer Perceptron with Backpropagation (MLPBP)	40
3.1:	IEEE 14-Bus Test Power System	52
3.2:	IEEE 30-Bus Test Power System	53
3.3:	IEEE 39-Bus Test Power System	54
3.4:	Flow Chart of The Voltage Instability Analysis Research Outline	55
3.5:	VSM (P) in PV Curve	58
3.6:	VSM (Q) in QV Curve	59
3.7:	LPM (P) in PV Curve	60
3.8:	LPM (Q) in QV Curve	61
3.9:	Diagram of A Neuron Model	66
3.10:	Optimized MLPBP-ANN Network	69
3.11:	Flow Chart of Voltage Instability Indices Predictions by MLPBP-ANN	70
3.12:	Basic Structure of ANFIS	72
3.13:	ANFIS Structure Simulated in MATLAB	75
3.14:	Flow Chart of Voltage Instability Indices Predictions by ANFIS	76
3.15:	Basic PNN Structure	79

3.16:	Flow Chart of Voltage Instability Indices Classifications by PNN	82
4.1:	VSM (P) Calculation Values for the IEEE 14-Bus Test Power System	85
4.2:	VSM (Q) calculation values for the IEEE 14-Bus Test Power System	86
4.3:	LPM (P) calculation values for the IEEE 14-Bus Test Power System	87
4.4:	LPM (Q) Calculation Values for the IEEE 14-Bus Test Power System	88
4.5:	VSM (P) Calculation Values for the IEEE 30-Bus Test Power System	90
4.6:	VSM (Q) Calculation Values for the IEEE 30-Bus Test Power System	91
4.7:	LPM (P) calculation values for the IEEE 30-Bus Test Power System	92
4.8:	LPM (Q) Calculation Values for IEEE 30-Bus Test Power System	93
4.9:	VSM (P) Calculation Values for the IEEE 39-Bus Test Power System	94
4.10:	VSM (Q) Calculation Values for the IEEE 39-Bus Test Power System	96
4.11:	LPM (P) Calculation Values for the IEEE 39-Bus Test Power System	97
4.12:	LPM (Q) Calculation Values for the IEEE 39-Bus Test Power System	98
4.13:	Participation Factor for The IEEE 14-Bus Power System (Q Modal Analysis Technique)	100
4.14:	Participation Factor for The IEEE 14-Bus Power System (P Modal Analysis Technique)	101
4.15:	Participation Factor for The IEEE 30-Bus Power System (Q Modal Analysis Technique)	103
4.16:	Participation Factor for The IEEE 30-Bus Power System (P Modal Analysis Technique)	104
4.17:	Participation Factor for The IEEE 39-Bus Power System (Q Modal Analysis Technique)	106
4.18:	Participation Factor for The IEEE 39-Bus Power System (P Modal Analysis Technique)	107
5.1:	Comparison Between the VSM (P) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 14-Bus Test Power System	115
5.2:	Comparison Between the VSM (Q) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 14-Bus Test Power System	117

5.3:	Comparison Between the LPM (P) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 14-Bus Test Power System	118
5.4:	Comparison Between the LPM (Q) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 14-Bus Test Power System	119
5.5:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting VSM (P) Values of the Weak Buses in the IEEE 14-Bus Test Power System	121
5.6:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting VSM (Q) Values of the Weak Buses in the IEEE 14-Bus Test Power System	122
5.7:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting LPM (P) Values of the Weak Buses in the IEEE 14-Bus Test Power System	124
5.8:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting LPM (Q) Values of the Weak Buses in the IEEE 14-Bus Test Power System	125
5.9:	Regression Analysis of VSM (P) Predictions for IEEE 14-Bus Test Power System.	127
5.10:	Regression Analysis of VSM (Q) Predictions for IEEE 14-Bus Test Power System	129
5.11:	Regression Analysis of LPM (P) Predictions for IEEE 14-Bus Test Power System	131
5.12:	Regression Analysis of LPM (Q) Predictions for IEEE 14-Bus Test Power System	133
5.13:	Comparison between MLBP-ANN and ANFIS VSM (P) Computing Time for IEEE 14-Bus Test Power System	135
5.14:	Comparison between MLBP-ANN and ANFIS VSM (Q) Computing Time for IEEE 14-Bus Test Power System	136
5.15:	Comparison between MLBP-ANN and ANFIS LPM (P) Computing Time for IEEE 14-Bus Test Power System	138
5.16:	Comparison between MLBP-ANN and ANFIS LPM (Q) Computing Time for IEEE 14-Bus Test Power System	139
5.17:	Comparison Between the VSM (P) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 30-Bus Test Power System	140

5.18:	Comparison Between the VSM (Q) Target and Prediction Values By MLPBP-ANN and ANFI	
5.19:	Comparison Between the LPM (P) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 30-Bus Test Power System	143
5.20:	Comparison Between the LPM (Q) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 30-Bus Test Power System	144
5.21:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting VSM (P) Values of the Weak Buses in the IEEE 30-Bus Test Power System	146
5.22:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting VSM (Q) Values of the Weak Buses in the IEEE 30-Bus Test Power System	147
5.23:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting LPM (P) Values of the Weak Buses in the IEEE 30-Bus Test Power System	148
5.24:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting LPM (Q) Values of the Weak Buses in the IEEE 30-Bus Test Power System	150
5.25:	Regression Analysis of VSM (P) Predictions for IEEE 30-Bus Test Power System	152
5.26:	Regression Analysis of VSM (Q) Predictions for IEEE 30-Bus Test Power System.	154
5.27:	Regression Analysis of LPM (P) Predictions for IEEE 30-Bus Test Power System	156
5.28:	Regression Analysis of LPM (Q) Predictions for IEEE 30-Bus Test Power System	158
5.29:	Comparison between MLBP-ANN and ANFIS VSM (P) Computing Time for IEEE 30-Bus Test Power System	160
5.30:	Comparison between MLBP-ANN and ANFIS VSM (Q) Computing Time for IEEE 30-Bus Test Power System	161
5.31:	Comparison between MLBP-ANN and ANFIS LPM (P) Computing Time for IEEE 30-Bus Test Power System	162
5.32:	Comparison between MLBP-ANN and ANFIS LPM (Q) Computing Time for IEEE 30-Bus Test Power System	164

5.33:	Comparison Between the VSM (P) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 39-Bus Test Power System	165
5.34:	Comparison Between the VSM (Q) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 39-Bus Test Power System	167
5.35:	Comparison Between the LPM (P) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 39-Bus Test Power System	168
5.36:	Comparison Between the LPM (Q) Target and Prediction Values By MLPBP-ANN and ANFIS for IEEE 39-Bus Test Power System	170
5.37:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting VSM (P) Values of the Weak Buses in the IEEE 30-Bus Test Power System	171
5.38:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting VSM (P) Values of the Weak Buses in the IEEE 30-Bus Test Power System	173
5.39:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting LPM (P) Values of the Weak Buses in the IEEE 39-Bus Test Power System	174
5.40:	Comparison of MSE Values Between MLBP-ANN and ANFIS in Predicting LPM (P) Values of the Weak Buses in the IEEE 39-Bus Test Power System	175
5.41:	Regression Analysis of VSM (P) Predictions for IEEE 39-Bus Test Power System	178
5.42:	Regression Analysis of VSM (Q) Predictions for IEEE 39-Bus Test Power System	180
5.43:	Regression Analysis of LPM (P) Predictions for IEEE 39-Bus Test Power System	182
5.44:	Regression Analysis of LPM (Q) Predictions for IEEE 39-Bus Test Power System	184
5.45:	Comparison between MLBP-ANN and ANFIS VSM (P) Computing Time for IEEE 39-Bus Test Power System	185
5.46 :	Comparison between MLBP-ANN and ANFIS VSM (P) Computing Time for IEEE 39-Bus Test Power System	186
5.47:	Comparison between MLBP-ANN and ANFIS LPM (P) Computing Time for IEEE 39-Bus Test Power System	188

5.48:	Comparison between MLBP-ANN and ANFIS LPM (Q) Computing Time for IEEE 39-Bus Test Power System	189
5.49:	Results of Bus 14 VSM (P) Training Data Classification by PNN	191
5.50:	Results of Bus 14 VSM (Q) Training Data Classification by PNN	194
5.51:	Results of Bus 14 LPM (P) Training Data Classification by PNN	196
5.52:	Results of Bus 14 LPM (Q) Training Data Classification by PNN	199
5.53:	Results of Bus 30 VSM (P) Training Data Classification by PNN	201
5.54:	Results of Bus 30 VSM (Q) Training Data Classification by PNN	204
5.55:	Results of Bus 30 LPM (P) Training Data Classification by PNN	206
5.56:	Results of Bus 30 LPM (Q) Training Data Classification by PNN	209
5.57:	Results of Bus 12 VSM (P) Training Data Classification by PNN	212
5.58:	Results of Bus 12 VSM (Q) Training Data Classification by PNN	215
5.59:	Results of Bus 12 LPM (P) Training Data Classification by PNN	217
5.60:	Results of Bus 12 LPM (Q) Training Data Classification by PNN	220

## LIST OF APPENDICES

APPENDIX	TITLE	PAGE
A	IEEE 14-Bus Test Power System Data	245
B	IEEE 30-Bus Test Power System Data	247
C	IEEE 39-Bus Test Power System Data	250
D	Electrical Power System Overview	253
E	Load Flow Analysis Basic Theory	255